

Device integration into AXING IPTV system

IPTV middleware

AXING AG
Gewerbehäus Moskau
8262 Ramsen
Switzerland



Supported TVs

Under <https://axing.com/en/produkte/iptvsolutions/technical-implementation/> you find the supported TV's or STB's for the AXING-IPTV system.

AXING ISW 9-43

The STB uses the same link as the most TVs <http://iptv-server.local/>.

So, when you use our DHCP server from the middleware, everything is working. But when you use your own DHCP server you must add a pointer from:

<http://iptv-server.local/> → IPTV server address

Samsung TV

On the remote control press the buttons in order:

“MUTE” “1” “1” “9” “OK”

Now the special hotel menu opens. Set the preferences as below:

- Hospitality Mode: Standalone
- Widget Solution
 - o Widget Mode: ON
 - o Solution Type: Vendor Server
 - o Server URL Setting: <http://iptv-server.local/mw/luxe/samsungTVE/?shade=user>

Device integration into AXING IPTV system

IPTV middleware

AXING AG
Gewerbehäus Moskau
8262 Ramsen
Switzerland

LG TV

On the remote control keep pressing the SETTING button until the black menu appears on the top of the screen and then:

"1" "1" "0" "5" "OK"

Now the special hotel menu opens. Set the preferences as below:

- LG Hotel Mode Setup: On
 - o Limited Mode: On
- Pro:Centric
 - o Mode: HTML
 - o Media Type: IP
 - o Server Address: IP Address
IP Address: 10.1.1.101 (This is the standard IP change it when you use another on)
Port Number: 80

LG STB

On the remote control keep pressing the SETTING button until the black menu appears on the top of the screen and then:

"1" "1" "0" "5" "MENU"

Now the special hotel menu opens. Set the preferences as below:

- LG Hotel Mode Setup: On
 - o Limited Mode: On
- Pro:Centric
 - o Mode: HTML
 - o Media Type: IP
 - o Server Address: IP Address
IP Address: 10.1.1.101 (This is the standard IP change it when you use another on)
Port Number: 80

Device integration into AXING IPTV system

IPTV middleware

AXING AG
Gewerbehaus Moskau
8262 Ramsen
Switzerland

Philips TV

On the remote control press the buttons in order:

"MUTE" "3" "1" "9" "7" "5" "3" "MUTE"

We recommend the service remote control for Philips TV's. Now the special hotel menu opens. Set the preferences as below:

- Dashboard
 - o Mode: Custom
 - o Custom Settings
 - Source: Server
 - Server Settings
 - Server URL: <http://iptv-server.local/mw/luxe/philipsTV/?shade=user>

Philips TV 5014 series

On the remote control press the buttons in order:

"MUTE" "3" "1" "9" "7" "5" "3" "MUTE"

In the settings menu please change the following options:

Switch on Settings

- Channel Settings
 - o Switch On Channel: None
- Feature Settings
 - o Switch On Feature: Dashboard

Guest Management

- Clear User Data: Standby and PowerOn

Dashboard

- Select Dashboard
 - o Custom Dashboard (Browser based)
 - Source
 - Server
 - Server Settings
 - Server URL: <http://iptv-server.local/mw/luxe/philipsTV5014/?shade=user>
 - Reload Dashboard After Network Restore: Yes
 - Fallback: On

Device integration into AXING IPTV system

IPTV middleware

AXING AG
Gewerbehau Moskau
8262 Ramsen
Switzerland

Advanced

- Professional Mode: On
- Power
 - o Power On: Standby
 - o Standby Mode: Fast
 - o Standby Delay: On
 - o Reboot Everyday: Off